



## TLED CIT2 Series LED T8 Bypass Lamp Fixture



### Applications:

The TLED CIT2 series is designed for single and doubled ended power LED tubes. Intended uses include parking garages, car washes, dairies, and food processing facilities. This luminaire is ideal for wet environments and areas that require hose-down cleaning.

### Build Details:

Heavy duty one piece compression molded polyester fiberglass housing with seamless polyurethane gasket. Polycarbonate latches standard, stainless steel latches are optional. 1/2" trade size knockouts on each end of the luminaire with weathertight plug included.

### Mounting:

Stainless steel mounting brackets. No holes required to be drilled in the housing. Optional stainless steel bail available for chain and cable hanging.

### Listing/Certifications:

ETL Listed UL 1598 for Wet Location  
NSF Certified  
IP65, 66, 67 Certified

## Ordering Matrix

TLEDCIT2	232	OC	WDS	NS
Family	Lamp/Nom Length	Lens	Reflector	Lamp Holder

### Family

**TLEDCIT2** = Tubular LED Citadel 2

### Lamp/Nominal Length

**132** = 1 Lamp 4' Nominal  
**232** = 2 Lamp 4' Nominal  
**332** = 3 Lamp 4' Nominal  
**1328** = 1 Lamp Tandem 8' Nominal  
**2328** = 2 Lamp Tandem 8' Nominal  
**3328** = 3 Lamp Tandem 8' Nominal

### Lens

**LR** = Lineal Ribbed Acrylic  
**OC** = Optically Clear Acrylic  
**PC** = Polycarbonate

### Reflector

**Blank** = No Reflector  
**S** = Standard Specular Reflector  
**WDS** = Wide Distribution Specular Reflector

### Lamp Holder

**S** = Shunted (double ended power)  
**NS** = Non Shunted (single ended)

### Options

**SL** = Stainless Latches  
**WH6** = 6ft 16AWG cord  
**OCC** = Wet Location Motion Sensor  
Extender Arm  
Order separately





# TLED CIT2 Series

## LED T8 Bypass Lamp Fixture

---

### Citadel 2 Installation

1. Securely attach mounting brackets (2) to mounting surface
2. Insert one side of the Citadel 2 housing into the mounting brackets.
3. Push up on the enclosure and then press in on the mounting bracket until the mounting bracket clicks into place.
4. Verify that the enclosure is fully supported before connecting to a power supply.

